RADIATION SURVEY WORKSHEET

eXaminer Radiation Survey Information

Airport:	T.F Green Airport	Scanner Location:	Baggage Handeling Room	Case#:	PVD-C356423
Personnel Performing Radiation Survey:	[redacted]			Date Survey Performed:	3/28/2011

Scanner Serial Number:	6755		Entrance Tunnel Serial Number:	1099		Exit Tunnel Serial Number:	1089-1B	
High Reading:	Average Reading:	Min. Reading:	High Reading:	Average Reading:	Min. Reading:	High Reading:	Average Reading:	Min. Reading:
45	13.04	3	61	18.76	4	59	21.52	3
Good			Good			Good		

Radiation Meter:	Type Meter:	451P	Meter Serial Number:	6230	Calibration Due Date:	February 1, 2012

NOTES

Complete Radiation Survey (CRS)	Record Voltage and Bean Current here:							
Rename this Document before starting the Survey to: PVD-CRS-28MAR2011-6755	Voltage:	165	KV	Beam Current:	10.0	mA		
	Maximum Safe Readings	Scanner	350	Tunnels	350	Curtains	350	

Step:	Procedure	Expected results
1.	Set Up: Obtain Inovision Ion Chamber Survey Meter and in an area away from the scanners, turn on the meter by pressing the On-Off key. Wait approx. 4 minutes for the meter to run through the initialization procedure.	The GUI will be visible and will indicate Standby. After the radiation meter initialization procedure is complete the meter will be reading less than 20 µR/hr and the meter will be ready for use.
2.	The scanner will be in Standby. Change the conveyor switch on the scanner to Stop. Change the exit tunnel conveyor switch to Off to stop the conveyor.	Both conveyors should be stopped.
3.	On the GUI dropdown screen, select diagnostic, followed by Radiation Survey. A radiation survey window will appear. Click “Turn On” button to turn x-rays on. Turn on x-rays prompt will say “Place survey bag on belt”. Place IQTK bag on Entry Conveyor Belt.	A window indicating “Radiation Survey” will appear.
4.	When “Bag in survey position” appears, go to the FCC monitor and select "2" then <Enter>, verify and record the voltage and current in the displayed on the FCC screen in the planks provided above.	The high voltage is between 144KV and 176KV. The current is between 8.8mA and 10.6mA and the scanner X-ray indicator lights are on.
5.	Survey one of the areas indicated by the boxes in Appendix A2. Record the highest reading within the area. Repeat the process until all areas are surveyed and readings are recorded.	As the survey is conducted, the radiation meter indicates the degree of radiation emission.
6.	Review all radiation data sheets for high readings.	Readings shall not exceed 350 uR/hr in any box.
7.	After radiation survey is complete, click on “Start Conveyor” button on the GUI. Click the “Turn Off” button to turn off x-rays. Next click “Done”. The IQTK bag will eject from exit tunnel. EDAC will reboot.	IQTK bag is ejected and scanner reboots.
7.	Visually inspect the entrance and exit of the system for X-ray caution hazard signs.	X-ray hazard signs reading “Do not insert any part of the body when system is energized” are posted at entrance and exit of system.
9.	Fill out the eXaminer radiation stickers and place on the eXaminer in accordance with Examiner Technical Bulletin ex253.	Readings shall not exceed 350 uR/hr in any box.

RADIATION SURVEY WORKSHEET



GOOD

Top View			
Scattered Radiation Measurement Points Worksheet			No PROBLEM
Record highest reading per panel		µR/Hr	
1	Exit Conveyor Top Panel	56	
2	Exit Conveyor Top Panel	59	
3	Exit Conveyor Top Panel	40	
4	Scanner Conveyor Top Panel	19	
5	Scanner Conveyor Top Panel	8	
6	Scanner Conveyor Top Panel	18	
7	Entrance Conveyor Top Panel	31	
8	Entrance Conveyor Top Panel	18	
9	Entrance Conveyor Top Panel	14	

Highest Reading	59
Average Reading	29
Lowest Reading	8

RADIATION SURVEY WORKSHEET

SIDE PROFILE VIEW (OPPOSITE AC)



SYSTEM - SIDE PROFILE VIEW (Opposite AC Side)			
Scattered Radiation Measurement Points Worksheet			No PROBLEM
Record highest reading per panel		µR/Hr	
1	Entrance Conveyor Panel	6	
2	Entrance Conveyor Panel	8	
3	Entrance Conveyor Panel	13	
4	Entrance Conveyor Panel	14	
5	Entrance Conveyor / Scanner Panel	5	
6	Upper Scanner Panel	13	
7	Middle Scanner Panel	7	
8	Lower Scanner Panel	12	
9	Upper Scanner Panel	3	
10	Middle Scanner Panel	8	
11	Lower Scanner Panel	4	
12	Exit Conveyor / Scanner Panel	45	
13	Exit Conveyor Panel	13	
14	Exit Conveyor Panel	17	
15	Exit Conveyor Panel	10	
16	Exit Conveyor Panel	12	

GOOD

Highest Reading	45
Average Reading	12
Low Reading	3

RADIATION SURVEY WORKSHEET

SIDE PROFILE VIEW (AC Side)



SYSTEM - SIDE PROFILE VIEW (AC Side)			
Scattered Radiation Measurement Points Worksheet			No PROBLEM
Record highest reading per panel		µR/Hr	
1	Exit Conveyor Panel	11	
2	Exit Conveyor Panel	8	
3	Exit Conveyor Panel	17	
4	Exit Conveyor Panel	3	
5	Exit Conveyor / Scanner Panel	43	
6	Upper Scanner Pane	15	
7	Middle Scanner Panel	15	
8	Lower Scanner Panel	9	
9	Upper Scanner Panel	14	
10	Middle Scanner Panel	13	
11	Lower Scanner Panel	10	
12	Entrance Conveyor / Scanner Panel	4	
13	Entrance Conveyor Panel	4	
14	Entrance Conveyor Panel	14	

GOOD

Highest Reading	43
Average Reading	13
Low Reading	3

RADIATION SURVEY WORKSHEET

SYSTEM - FACES (End Views)



eXaminer entrance

eXaminer exit

SYSTEM - FACES (End Views)			
Scattered Radiation Measurement Points Worksheet Record highest reading per panel		µR/Hr	No PROBLEM
1	Scanner Panel	4	
2	Scanner Top Panel	7	
3	Scanner Panel	13	
4	Belt Entrance	61	
5	Entrance Lower Panel	14	
6	Belt Lower Facia Cover Entrance	41	
7	Scanner Panel	6	
8	Scanner Top Panel	9	
9	Scanner Panel	3	
10	Belt Exit	9	
11	Exit Lower Panel	8	
12	Belt Lower Facia Cover Exit	18	

GOOD

Highest Reading	61
Average Reading	16
Low Reading	3